

SYSTEM AND METHOD FOR CLEANING SEMICONDUCTOR FABRICATION EQUIPMENT PARTS

By Inventor

Samantha Tan

CROSS REFERENCE TO RELATED APPLICATIONS

This application claims the benefit of provisional application U.S. Serial No.-60/224/582 (Atty. Docket No. 60081-300500), filed on August 11, 2001, entitled "System and Method for Cleaning Semiconductor Fabrication Equipment Parts", incorporated herein by reference.

BACKGROUND OF THE INVENTION

The commercial fabrication of semiconductor chips is performed on silicon wafer substrates, which are typically four to twelve inches in diameter. There are often more than 100 processing steps in the fabrication of semiconductor chips including oxidation, diffusion, ion implantation, deposition of conductors and insulators, photolithography, and etching. Various conducting and insulating layers are deposited uniformly over the wafer to a thickness of a few microns.

In critical applications, certain new parts of semiconductor processing equipment need to be cleaned prior to installation and use in order to remove residual contamination from the machining or manufacturing process in order to achieve levels of cleanliness similar to the semiconductor wafer itself. Furthermore, after many wafers have been processed, the equipment used in the semiconductor processing process becomes contaminated, and therefore unusable. For example, in an etching machine, polymer deposits on the outer circumference of electrodes or chucks supporting the wafers until it becomes thick enough to interfere with the wafer's contact with the electrode. This results in non-uniform etching across the wafer as well as missed transfers due to a wafer sticking to polymer buildup on the electrode. Non-uniformity exceeding seven percent is beyond some specified limits, in turn affecting side wall profile variance across the wafer. In addition, other components in the equipment chamber e.g. roofs/domes and liners are also coated with polymers and contaminants which contribute particles, metallic and organic impurities to the wafers.

Therefore, it is then necessary to disassemble the parts in the equipment chamber and clean the individual parts.

Generally, semiconductor manufacturing plants employ specialized cleaning houses to have the semiconductor processing equipment parts cleaned. These cleaning houses typically clean the equipment by following "recipes," given to them by the manufacture of the equipment. These recipes generally include information informing the cleaning house how to clean the parts. Since, there are many variations to the wafer processes, the polymer and contamination levels of a used chamber part is different, therefore, merely following one cleaning recipe does not always result in the part being cleaned. In addition, after following the cleaning recipe, a conventional cleaning house generally will not test the parts to ensure its cleanliness. In general, a conventional cleaning house has no idea as to the effectiveness of the cleaning process provided to them in the recipe.

The result of following cleaning recipes in this manner, is that many semiconductor parts are returned to the semiconductor manufacturing plant still contaminated with unacceptable levels of impurities. This results in contamination that may be transferred onto a wafer typically in the form of high particle counts, or in inoperable equipment that must again be disassembled for re-cleaning, thus further increasing the down time for the equipment.

In view of the forgoing, what is needed are methods and systems for enhanced cleaning and certification of semiconductor fabrication equipment. The methods should be flexible, and consistent enough to minimize or eliminate contamination from the equipment, to improve the mean time between cleanings (MTBC), to improve the number of RF hours run on a chamber set of parts and to reduce the downtime experienced by most semiconductor fabrication equipment.

With the ability to test and verify the effectiveness of cleaning procedures, new cleaning methods can be developed for critical chamber parts. Critical chamber parts are usually constructed from base materials such as ceramics (Al_2O_3 , SiC , AlN) and quartz (SiO_2). Chamber parts manufactured from these base materials are very expensive and are selected because of they are non-contaminating with respect to

metallics, organics and particles. With new cleaning methods, these critical chamber parts can be effectively cleaned and recycled to reduce manufacturing cost.

Typically, in the prior art, relatively high concentrations of acids and other cleaning agents were used to clean parts. For example, a typical acid bath for quartz
5 cleaning would include 1 part HF, 1 part HNO₃, and 1 part H₂O. Unfortunately, such high concentration solutions suffer from a number of drawbacks. For one, they can damage the surface of part being cleaned by scoring, etching, pitting, etc. Further, these high concentration solutions tend to be expensive, hazardous, and difficult to dispose of.

10

11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203
2204
2205
2206
2207
2208

SUMMARY OF THE INVENTION

The present invention addresses these needs by providing a process for enhanced semiconductor fabrication equipment and parts cleaning. In one embodiment, a definition is determined that defines the characteristics for a clean part. Next, a part to be cleaned is tested to determine its incoming impurity levels. A cleaning process is then determined that is capable of reducing the incoming impurity levels for a particular part, depending on the type of base material the part is made from, the deposits on the part, and characteristics of adhesion, particle generation and reactivity. The appropriate cleaning process is then applied to the part so that it reduces the incoming level of impurities on the part, and tested to ensure that the part is clean. There are various types of impurities, but typically they fall into the categories of metals, particles, and organic organics.

Advantageously, one embodiment of the present invention reduces the cleaning defects by use of repeated testing of the impurity levels after each pass through the cleaning process. Moreover, by knowing the characteristics of a clean part through testing, the process of the present invention can achieve particular impurity level goals with increased accuracy, and the part can be certified to meet an actual specification based on either the need for cleanliness in the semiconductor process, or based on statistically significant test data. Finally, the process may be continuously optimized to further enhance the cleaning process by direct testing of the cleanliness of the part, by correlating to number of "added" particles and RF hours that the parts can be used before particles increase to unacceptable limits, and ultimately by correlating to improved wafer yield.

Using the dual concepts of in-process testing of the cleanliness of a part for improved cleaning performance, and testing the cleaned part after the final cleaning, a cleaning method can be customized, optimized, and validated for each critical part.

Advantageously, dilute chemistries can be used in preferred embodiments of the present invention. This makes the cleaning process less expensive. Used chemicals are also easier to dispose of because the percentage of acids is much lower which also in turn makes it less hazardous. Additionally, there is less damage to the

product. The present invention further includes methodologies to determine optimal chemistries which are effective, yet dilute.

These and other advantages of the present invention will become apparent upon a study of the following descriptions and related drawings.

5

CMTRP005A/PLH/JP

BRIEF DESCRIPTION OF THE DRAWINGS

Figure 1A is a flowchart showing a general process guideline for cleaning semiconductor fabrication equipment parts.

5 Figure 1B is a flowchart showing a process for cleaning semiconductor fabrication equipment parts, for example high purity quartz, in accordance with an embodiment of the present invention.

Figure 2 is a flowchart showing a process for cleaning high purity quartz in accordance with another embodiment of the present invention.

10 Figure 3 is a flowchart showing a surface particle test process for impurity level testing of a new or clean part, in accordance with one embodiment of the present invention.

Figure 4 is a flowchart showing a liquid particle test process of a new or clean part, in accordance with an embodiment of the present invention.

15 Figure 5 is a flowchart showing an acid extraction/ICP-MS technique of a new or clean part, in accordance with an embodiment of the present invention.

Figure 6 is a flowchart showing a cleaning process 110, in accordance with one aspect of the present invention, to remove resistant organic polymer and metallic impurities from a high purity ceramic dome.

20 Figure 7 is a flowchart showing a cleaning process 110, in accordance with one aspect of the present invention to remove particle from a textured high purity quartz surface.

Figure 8 is a flowchart showing a cleaning process 110, in accordance with one aspect of the present invention to remove particle and metallic impurities from a
25 textured high purity ceramic (>99% Al₂O₃) surface.

The invention, together with further advantages thereof, may best be understood by reference to the following description taken in conjunction with the accompanying drawings.

DETAILED DESCRIPTION OF THE INVENTION

An invention is described herein for cleaning semiconductor equipment parts
5 (such as CVD and etch chamber parts) that achieve increased effectiveness in
impurity removal. In the following description, numerous specific details are set forth
in order to provide a thorough understanding of the present invention. It will be
apparent, however, to those skilled in the art, that the present invention may be
practiced without some or all of these specific details. In other instances, well known
10 process steps have not been described in detail in order not to unnecessarily obscure
the present invention. In particular, this includes most of the analytical testing
methods used to measure or confirm impurity levels.

In accordance with one aspect of the present invention, the aforementioned
metallic impurity removal is substantially enhanced by the use of a new chemical
15 formula in the various cleaning processes. This cleaning formula is particularly novel
as applied to the cleaning of polysilicon, quartz, and ceramic parts (Al_2O_3 , SiC and
AlN) for which it has proven to be quite effective. Specifically, the cleaning formula
is a composition of high purity hydrofluoric acid (HF), nitric acid (HNO_3), and
hydrogen peroxide (H_2O_2), in very dilute quantities. Preferably, the composition
20 includes 0.5-1.5%wt. HF, 0.1-0.5%wt. HNO_3 , and 1-10%wt. H_2O_2 . This particular
formula results in a particularly efficient collector of metals on certain materials as
described in greater detail subsequently. This high purity cleaning and collection
solution has been shown to have very high recoveries and efficiencies, especially on
single crystal silicon wafer surfaces, high purity quartz, polysilicon, and ceramics.
25 Previously, these materials were cleaned with concentrated chemicals mixtures of
 HF/HNO_3 , and HCl/HNO_3 at much higher concentration of 10%-40%wt for each
chemical. The chemical H_2O_2 is not employed in these mixtures. The high
concentrations of the chemical mixtures did not improve metallic removal and can
severely etched and damaged the base materials. It is shown that the high purity dilute
30 chemical formula in this invention is highly effective in removing metallic
contaminants and will not etch any of the aforementioned base materials for more
than a few hundred angstroms.

It will therefore be appreciated that a dilute aqueous cleaning solution for parts can be made up of 0.5 – 1.5%wt. HF, 0.1-0.5%wt. HNO₃ and 1-10%wt H₂O₂. The concentration of H₂O₂ can also be no greater than about 5%wt.

5 Metallic contaminants form bonds with the surfaces of the semiconductor fabrication equipment parts, thus bonding the metal impurities to the surfaces of the equipment. These chemical bonds create increased difficulty in cleaning the parts without the use of correct chemical formulations. If the chemical formulations are too concentrated, the semiconductor equipment parts can be irreversibly destroyed or are not sufficiently cleaned.

10 The chemical formula of the present invention substantially enhances the cleaning process by breaking the chemical bonds and thereafter collecting the metal impurities. To elaborate further, the hydrofluoric acid breaks silicon and aluminum bonds by dissolving the silicon and aluminum oxides of the surface of the semiconductor equipment. This frees the metal impurities and allows them to be
15 collected in the cleaning solution. It should be borne in mind that the amount of hydrofluoric acid must be carefully controlled, as too much hydrofluoric acid results in damage to the surface of the equipment parts. The use of HF is critical in semiconductor parts cleaning because silicon and aluminum oxides are prevalent impurities in all types of parts.

20 The hydrogen peroxide is a strong oxidizer and is used to convert the metals such as Cu, Au and Ag into the soluble forms. Therefore, the presence of H₂O₂ greatly increases the range of metal impurities that can be removed from a surface.

Finally nitric acid is used to stabilize and increase the solubility of some metal impurities so that insoluble fluorides of Ca and Mg are kept in the solution and away
25 from the surface of the semiconductor equipment parts. In this technique, it is preferable to have the solution as dilute as possible, yet still effective to clean the equipment parts to predefined specifications. The above mentioned ranges are thus the preferred minimums needed to clean the equipment.

30 The chemical formula of the present invention is used to perform various cleaning processes for semiconductor equipment parts and other high purity material applications. In one embodiment, this formula has been shown to be quite effective in

cleaning metal ions from high purity quartz, as is commonly found as rods, tubes, crucibles, domes, chambers and bell jars. In another embodiment, this formula has been shown to be quite effective in cleaning metal ions from high purity polysilicon and single crystal silicon surface, as is commonly found in chamber roofs, source rings, collars and wafers respectively. In another embodiment, this formula has been shown to be quite effective in cleaning metal ions from high purity ceramic materials Al_2O_3 as found in chamber domes, bell jars, rings, gas nozzle assemblies and wafer chucks; SiC as found in chamber roofs, domes, rings and collars; and AlN as is commonly found in wafer chucks.

In accordance with another aspect of the present invention, the aforementioned particle impurities are removed from the semiconductor equipment surface by chemical treatments. Most semiconductor equipment parts fabricated from the aforementioned critical base materials are textured by grit blasting in order to improve process polymer adhesion. After machining and texturing, the parts are cleaned to remove particles. There are two categories of particles on the textured surface. The first type is surface particles that are loosely adhering. These particles can be removed physically by a short ultrasonication step. The origin of the second category of particles is less obvious. These particles originated from the weakened base material surface caused by texturing. In the process chamber, sub-surface damages are often exaggerated during wafer processing causing particle shedding.

The chemical formula of the present invention significantly reduces the particles from textured equipment parts by etching off a layer of damaged base materials without affecting the desired surface roughness. First, the depth of the subsurface damage is determined using any one of a number of well-known techniques. Using concentrated basic solutions such as 10-30 %wt KOH and NaOH in water, base materials such as polysilicon base materials can be etched off to a predetermined depth (i.e. to about the depth of the measures subsurface damage) by controlling temperature and time to remove all the sub-surface damages. Using concentrated acidic solutions such as $\text{H}_2\text{SO}_4/\text{H}_2\text{O}_2$ and $\text{H}_2\text{SO}_4/\text{H}_3\text{PO}_4$ in the range of 10-50 %wt for each chemical, ceramic materials (Al_2O_3 , SiC and AlN) can be etched off to a predetermined depth by controlling temperature and time to removed all the sub-surface damages. In another application with quartz, the use of HF/HNO_3 , 20-40

% wt for each chemical in water, used with ultrasonic energy (27-120 kHz) for 10-20 mins is found to effectively etched off damaged quartz material resulting from grit-blasting and particle counts can thereby be drastically decreased.

In accordance with another aspect of the present invention, the
5 aforementioned organic polymer deposited on semiconductor equipment surface during wafer processing can be removed from all type of critical materials surface by a thermal decomposition step. Organic polymers are often found in etch equipment parts. These organic polymers can be efficiently removed by submitting dirty quartz and Al₂O₃ parts to a high temperature of 600 – 800 °C for 1-10 hours depending on
10 how thick or resistance the organic polymer to cleaning. A high temperature muffle furnace is used for this purpose.

In another embodiment, disassembled semiconductor fabrication equipment parts are subjected to cleaning processes and testing to achieve enhanced impurity removal, as described in greater detail subsequently.

15 Figure 1A is a flowchart showing a general process guideline 5 for cleaning semiconductor fabrication equipment parts. The process starts at operation 10 and proceeds to operation 20 where a baseline chemistry is developed for cleaning the part. In operation 30, the part is cleaned with the baseline chemistry. In operation 40, the effectiveness of the cleaning process is tested. If it is not sufficient, operation 50 is
20 performed where the chemistry is adjusted to improve the cleaning ability and the part is re-cleaned at operation 30. If the first cleaning was effective, the process ends at operation 60.

In operation 50, the chemistry can be adjusted in various ways. For example, the chemistry can be changed by adding or deleting acids, oxidizers, etc. It can also
25 be adjusted by increasing the concentration of the solution, or by making the solution more dilute. The purpose of operation 50 is, therefore, to optimize the chemistry to provide the most effective, least damaging, most economical, and least hazardous solution to cleaning the part.

Figure 1B is a flowchart showing a process 100 for cleaning semiconductor
30 fabrication equipment parts, for example high purity quartz, in accordance with an embodiment of the present invention. In an initial operation 102, pre-process

operations are performed. Pre-process operations include preparing and testing facility configurations and other pre-process operations that will be apparent to those skilled in the art. In particular, pre-process operations can include establishing environmental controls (e.g. particles and metals in the environment), qualifying
5 RO/DI high purity water, establishing "new" handling protocols, and setting up fixturing process.

In a specification operation 104, the specification for what constitutes a clean part is determined. As indicated previously, conventional cleaning houses generally follow a recipe given to them by a manufacturer. For example, a cleaning recipe from
10 a manufacturer may include rinsing a part in deionized water, immersing it in a particular chemical mixture, etc. In the present invention, instead of merely following a cleaning recipe, a specification for a clean part is determined. The specification characterizes what the minimum parameters are for a particular part to be considered clean enough to achieve the required wafer performance.

15 A specification may be obtained from another party, such as the party owning the part to be cleaned, or the specification may be determined by testing. There are three ways to create a specification through testing. In the first approach a part is first obtained that is already known to be clean, i.e., has the minimum parameters to be considered clean, for example a new part. The part is then tested and characterized
20 with respect to particles, metals, organics, or any combination thereof. When characterizing with respect to particles, the surface of the part is examined with respect to particles using several different analytical techniques which may include the Dryden QIII surface particle counter, a liquid particle counter (LPC), or Scanning Electron Microscopy (SEM) or SEM with Energy Dispersive X-ray detection
25 (SEM/EDX). When characterizing with respect to metals, the surface is examined through sophisticated analytical chemistry testing methods with respect to surface metal contamination, bulk metal contamination, or both. When examining the part with respect to bulk metal contamination, a portion of the material is digested in a solution to measure the impurities within the material. With respect to surface metal
30 contamination, metals are extracted from the surface, normalized to the surface area, and measured by spectroscopic techniques such as inductively coupled plasma-mass spectrometry (ICP-MS). When characterizing the part with respect to organics,

surface extractions may be made using DI and solvents that are then analyzed by a total organic carbon analyzer (TOC) and Gas Chromatography (GC) or Gas Chromatography with Mass Spectrometry (GCMS) respectively. Alternately or additionally, the entire material may be outgassed at a high temperature with the
5 resulting gasses being analyzed by dynamic head space GC-MS or ATD GC-MS.

In the second approach, new or used parts are cleaned using the best known cleaning methods based on historical or theoretical considerations. After the cleaning process is applied, the part is tested for impurities. The part is then assembled into the semiconductor process equipment and chamber process data is collected. Process
10 data may include 1) particles added ("adders") to a silicon wafer surface after being in contact with the process equipment containing the clean part; 2) metal impurities transferred onto a silicon wafer surface after being processed in the semiconductor equipment containing the clean part; 3) mean number of wafers between cleanings; etc. Such chamber process data can then be correlated to analytical impurity test data
15 from the cleaned part itself. In this way cleaning methods and formulas can be developed or improved based on the correlation between the test data from the analytical impurity testing on the part and the data generated after running a wafer in the process chamber. Moreover, a specification can be set after evaluation of the chamber process performance parameters.

20 In the third approach, specifications can be set by collecting impurity test data on a statistically significant number of parts that has proven to perform well in the semiconductor process. Control limits can also be established by collecting test data on a statistically significant number of parts.

Next, in an operation 106, the incoming impurity level for the part is
25 determined. In this operation, a part is tested to determine the current impurity level of the part with respect to metals, particles, or organics. For particles, this determination is made by performing either a surface particle test or a liquid particle count test, as described in greater detail subsequently. Depending on the type of test utilized to determine the particle level, the particle impurities are described as either
30 particles per cm^2 or particles per volume of solution. The incoming trace metal impurities are typically measured using acid extraction ICP-MS technique, the metallic levels are described as atoms/ cm^2 or ng/ cm^2 . The incoming impurity levels

for organics are measured using GC, GCMS, or ATD GCMS and the organic levels are described as atoms/cm² or ng/cm² for trace concentration or % surface concentration for major concentration. SEM/EDX maybe used semi-quantitatively for the determining of major elements such as those present in the process polymers, the elements being C, F, Cl, Al Si and O.

In a surface determination operation 108, the surface of the part is characterized. Generally, this operation determines the characteristics of the material. These characteristics include the desired surface finish as well as surface roughness.

Referring next to operation 110, a mechanical and chemical process that will meet the clean specification of the part is determined. Depending on the material, size, condition, and specification of the part being cleaned, a mechanical and chemical process is determined that will clean the part to the predefined clean specification of operation 104. For example, a process for cleaning a quartz part is disclosed subsequently. Once determined, the chemical and/or mechanical processes are applied to the part.

After cleaning, the part is again tested to determine the impurity level of the part, in operation 112. This operation is performed much the same as operation 106, the difference being that operation 112 is carried out after the part is cleaned.

A determination is then made as to whether the clean specification has been met, in operation 114. Essentially, the results of the impurity level determination operation 112 are compared to the specification, determined in operation 104. If the specification has been met, the process continues with an equipment testing operation 116. However, if the specification is not met, the process continues with another process determination operation 110.

Thus, the present invention, with respect to metal impurities, utilizes a sequential approach to cleaning semiconductor equipment parts. In this manner, the cleaning process is repeated until the impurity level is brought down to an acceptable level. Essentially, the impurity levels are brought down by orders of magnitude in a stepwise fashion. In addition, the cleaning processes can be optimized with each pass through the process, based on the measurement of the impurity levels.

In an equipment test operation 116, the clean equipment part is installed and operated with the process for manufacturing semiconductor devices and the wafers are measured for contaminants after being run in the process as an indication of the purity of the materials in the chamber. Particularly, the number of particles added to the wafer after running the process and the impurities on the wafers are considered indicies.

A decision is then made as to whether the part functions properly in its related equipment, in operation 118. If the part functions properly, the process is completed in a finishing operation 120. Otherwise, the process continues with another process determination operation 110.

Finally, in a finishing operation 120, the cleaning process is completed and the cleaned part may be put back into production. Advantageously, the present invention reduces cleaning defects by repeated testing of the impurity levels after each pass through the cleaning process. Moreover, by knowing the characteristics of a clean part, the process of the present invention can achieve specified results with increased accuracy. Finally, the cleaning process may be continuously optimized to achieve a cleaning process that cleans close to 100 % of the parts from a particular process.

An important feature of the present invention is the use of analytical testing. As described previously, conventional cleaning is done with little or no testing of the part itself. The most testing typically done in conventional cleaning is testing of the resistivity of the rinse water used in a conventional cleaning process or of the concentrations of the acid baths. In contrast, the present invention consistently test the impurity levels of the semiconductor parts after being cleaned, as described in greater detail with respect to Figure 3.

In view of the foregoing, it will be appreciated that a process for cleaning semiconductor fabrication equipment parts includes determining a definition for a clean part including multiple maximum acceptable impurity levels, determining an initial multiple impurity levels of a part prior to its cleaning, determining a cleaning process to apply to the part, applying the cleaning process to the part, wherein the cleaning process creates reduced multiple impurity levels for the part below that of the initial multiple impurity levels, determining the reduced multiple impurity levels,

comparing the reduced multiple impurity levels against the multiple maximum acceptable impurities levels of said definition, and repeating the application of the cleaning process to the part if said reduced multiple impurity levels do not meet the definition of a clean part.

5 The process can also include testing the part in reassembled equipment in which the part was designed to operate and repeating a cleaning process on the part if the part does not function properly in the reassembled equipment.

Also the process can include at least one impurity level which is determined utilizing a surface particle test. The impurity level can also be determined by using a
10 liquid particle test. Also, one or more impurity levels can be determined by using acid-extraction ICP-MS technique..

Figure 2 is a flowchart showing a process for cleaning high purity quartz in accordance with another embodiment of the present invention. Figure 2 shows a process 200 that progresses through the following acts or operations. In 210 the part
15 is degreased with solvents such as IPA/acetone and is sprayed rinse with DI water or alternately ultrasonicated in DI water. In 212 the part is cleaned by either a spray or squirt rinse with the aforementioned high purity cleaning formula. In 214 the cleaning solution used in 212 is discarded. In 216 the acts or operations of 212 and 214 are repeated, where the number of repeats is a function of specification level of
20 purity. In 218 another DI water ultrasonication and spray rinse of the quartz part is performed. In 220 the part is allowed to dry under heat lamps within a controlled HEPA/ULPA filtration cleanhood located in a cleanroom. In 222 testing is performed for surface metals and/or surface particles. In 224 impurity data is collected. And in 226 the quartz part is packaged in a cleanroom or similar controlled
25 environment.

It will therefore be appreciated that a method for reducing sub-surface damage to a part includes determining how deep is the sub-surface damage beneath a surface of a part, chemically etching the surface of the part and stopping the chemical etching of the surface at about the depth of the sub-surface damage.

30 Also, a method for cleaning a part includes performing an ultrasonication cleaning process to a surface of a part to be cleaned, spray rinsing the part with a

dilute chemical mixture and spray rinsing the part with deionized water. The method can also include repeating the spray rinsing of the part with a dilute chemical mixture and spray rinsing the part with deionized water based upon the specification of purity for the part.

5 Figure 3 is a flowchart showing a surface particle test process 300 for impurity level testing of a new or clean part, in accordance with one embodiment of the present invention. In an initial operation 301, pre-process operations are performed. Pre-process operations include determining the specification of characteristics for a clean part, and other pre-process operations that will be apparent to those skilled in the art.
10 This process is applicable, for example, to operations 1-6 and 112 of Fig. 1.

Next, in a cleanroom operation 302, the semiconductor equipment part to be measured is opened in a class 1000 cleanroom or better (1000 particles per cubic centimeter). Upon being disassembled, semiconductor equipment part is packaged for delivery to the cleaning center. To avoid further contamination of a new or clean part,
15 it is preferable to open the part in a controlled clean environment. In 304 the input of the particle counter is scanned over the part over a specified distant. In 306 an analysis of the part is begun using clean handling techniques. In 308 impurity data is collected after stabilization, and in 310 the data is processed. The process is completed in 312.

20 Figure 4 is a flowchart showing a liquid particle test process 400 of a new or clean part, in accordance with an embodiment of the present invention. In an initial operation 401, pre-process operations are performed. Pre-process operations include determining the specification of characteristics for a clean part, and other pre-process operations that will be apparent to those skilled in the art. This process is applicable,
25 for example, to operations 1-6 and 112 of Fig. 1.

Next, in a cleanroom operation 402, the semiconductor equipment part to be cleaned is opened in a cleanroom. Upon being disassembled, semiconductor equipment is packaged for delivery to the cleaning center. To avoid further contamination of the part, it is preferable to open the part in a controlled clean
30 environment.

In a UPW control operation 404, the particles currently present in the ultra pure water are measured. The liquid particle test process 400 uses ultra pure water (UPW) as the carrier medium to determine the impurity level for a particular semiconductor equipment part. As a control, the level of particles present in the UPW is determined before the part is placed in the water. Subsequently, the new part can be ultrasonicated to dislodge particles that are adhered to its surface into the UPW. The UPW can then be retested, with the particle count difference being attributable to the part itself.

In a UPW application operation 406, a known volume of the UPW is applied to a cavity of the part to be analyzed. The cavity of the part is essentially the area of the part which provides the best test area for analyzing the impurity level of the part.

Next, in a UPW extraction operation 408, the UPW is extracted from the part and introduced into a liquid particle counter. After introducing the UPW to the cavity of the part, the UPW gathers particles from the surface of the part. Thus, by knowing the particle level of the UPW before being introduced into the cavity of the part, and then measuring the amount of particles in the UPW after being introduced into the cavity of the part, the impurity level of the part can be determined.

The analysis of the impurity level for the part is then begun, in an analysis operation 410.

Then, after the liquid particle counter stabilizes, the impurity level data is collected, in a data collection operation 412. Initially, the data is collected in particle size. Thereafter, the data is normalized over the surface area of the semiconductor part being analyzed.

The impurity level data is then processed in a data processing operation 414. The particles are measured both in terms of size distribution and quantity. The quantity could be in thousands of counts down to single digits. The distribution can be as low as about 0.05 microns up to about 10 microns. Preferably, the particle counts are "bucketed" into specified size ranges of interest to assist in analysis. The result is the number of particles per volume of solution or particles per cm^2 .

Finally, post-process operations occur in operation 416. Post-process operations include using the impurity level information to aid in further processing of the part and other post-process operations that will be apparent to those skilled in the art.

5 In view of the foregoing, a method for determining contamination of an openable part having inner surfaces includes introducing a part into a controlled clean environment of at least class 1000, opening the part in the controlled clean environment and running contamination analysis on the inner surfaces of the part.

The method can also include applying a known volume of ultra pure water to a cavity of a part, extracting the water, and analyzing contaminants found in the water. The method can additionally include applying a known volume of a high purity extraction solution to a cavity of a part, extracting the extraction solution, and analyzing contaminants found in the extraction solution.

Figure 5 is a flowchart showing an acid extraction /ICP-MS technique 500 of a new or clean part, in accordance with an embodiment of the present invention. In an initial operation 501, pre-process operations are performed. Pre-process operations include determining the specification of characteristics for a clean part, and other pre-process operations that will be apparent to those skilled in the art. This process is applicable, for example, to operations 1-6 and 112 of Fig. 1.

20 Next, in a cleanroom operation 502, the semiconductor equipment part to be cleaned is opened in a cleanroom. Upon being disassembled, semiconductor equipment is packaged for delivery to the cleaning center. To avoid further contamination of the part, it is preferable to open the part in a controlled clean environment.

25 In an acidic extraction control operation 504, the analytical test process 500 uses a high purity extraction solution (e.g. 1.25 %wt HF, 3 %wt H₂O₂ and 0.125 % wt HNO₃) to determine the metallic impurity level for a particular semiconductor equipment part. As a control, the level of metallic impurities present in the extraction solution is determined by ICP-MS. Subsequently, a selection area of the new part is extracted with the high purity extraction solution. The extract is then retested, with the metallic level difference being attributable to the part itself.

In a operation 506, a known volume of the high extraction solution is applied to a cavity of the part to be analyzed. The cavity of the part is essentially the area of the part which provides the best test area for analyzing the impurity level of the part.

Next, in a operation 508, the high purity extraction solution is extracted from the part and introduced into an ICP-MS. After introducing the high purity extraction solution to the cavity of the part, the extraction solution gathers metallic impurities from the surface of the part. Thus, by knowing the metallic level of the extraction solution before being introduced into the cavity of the part, and then measuring the amount of particles in the extraction solution after being introduced into the cavity of the part, the impurity level of the part can be determined. The acid extraction /ICP-MS technique is then completed with operation 510.

The analysis of the impurity level for the part is then begun, in an analysis operation 510.

Then, after the ICP-MS stabilizes, the impurity level data is collected, in a data collection operation 512. Initially, the data is collected in ppbw (parts per billion wt). Thereafter, the data is normalized over the surface area of the semiconductor part being analyzed.

The impurity level data is then processed in a data processing operation 514. The metallic impurities are measured both in terms of concentration in ppbw for each type of trace metals. The area of the part that is extracted is calculated and the result is normalized atoms per cm^2 or ng/cm^2 .

Finally, post-process operations occur in operation 516. Post-process operations include using the impurity level information to aid in further processing of the part and other post-process operations that will be apparent to those skilled in the art.

Figure 6 is a flowchart showing a cleaning process 600, in accordance with one aspect of the present invention, to remove resistant organic polymer and metallic impurities from a high purity ceramic dome ($>99\% \text{Al}_2\text{O}_3$). In an initial operation 601, pre-process operations are performed. Pre-process operations include

determining the particular characteristics of the part to be processed and other pre-process operations that will be apparent to those skilled in the art.

In operation 602, the ceramic dome is DI water sprayed rinse to remove loose polymers, particles and metallic impurities. Initially, the ceramic dome is unpacked, recorded, and photographed to record the initial condition of the dome. The ceramic dome is then placed in a chemical bath 603 for about 2 hours. The chemical bath is preferably an dilute HF/HNO₃ chemical bath, which is heated to about 60-80°C. The concentration of HF is less than 5% wt and HNO₃ is less than 10 %wt. The hot acid dissolves Si-O and Al-O bonds and breaks other metallic bonds. Thereafter it is removed from the chemical bath, DI spray rinsed and dried with a cleanroom wipe or with a heat lamp until no moisture is observed on the inside or outside of the dome. It has been found to be very important to do the pre-treatment step 603 before putting the part into the furnace in order to dissolve the Si-O and Al-O bonds. This advantageously reduces the amount time the part has to be in the furnace of the next operation.

In a heating operation 604, the dome is heated in a furnace. In this operation, the dome is placed in a furnace and heated to about 700-800°C for about 6-12 hours. After about 6-12 hours, the furnace is turned off. To avoid damage to the dome, the furnace should generally not be opened until the temperature reaches below 200°C. Opening the furnace earlier may result in the dome being cracked. After the temperature reaches below 200°C, the furnace may be opened and allowed to cool to below 80°C. The dome is then withdrawn from the furnace when the temperature reaches below 80°C.

Next, in a bath operation 606, the dome is placed in another chemical bath. The chemical bath is also an HF/HNO₃ chemical bath, which is heated to about 80°C. The concentration of HF and HNO₃ is the same as the first bath but is kept clean and is prepared from higher purity chemicals. The dome is placed in the chemical bath for about 6-8 hours to dissolve any residual carbon and silicon /aluminum oxides and any other metallic impurities. After this step, it is placed in an acid waste tank and rinsed with deionized water to remove any residual acids. Thereafter, the dome is preferably visually inspected 607 to determine the cleanliness of the part. If organic polymer is still observed, the operations 604/606 are repeated.

In an ultrasonication operation 608, the dome is ultrasonicated in deionized water. Once a visual inspection has been made of the dome, it is ultrasonicated in a fresh overflowing deionized water bath for about two hours. In the operation 610, the dome is tested by LPC technique. As stated previously, this impurity testing operation helps in determining whether the part has been cleaned to have characteristics in accordance with the predetermined clean specification. If the particle level as measured by LPC technique is less than 400,000 particle per cm^2 , the dome is then rinsed in deionized water approximately 10 times, and thereafter purged dry with filtered N_2 and further under a heat lamp 611 for at least 1 hour. The process 608 can be repeated if the dome has not attained the specified levels of impurity

The part is then further tested for impurities, in a testing operation 612. Preferably, a surface particle test is performed on the dome using a Dryden QIII particle counter. After testing adequately to the predetermined specification, the part is packaged with cleanroom double bags in the cleanroom.

Finally, in operation 614, various post-process operations are performed. Post-process operations include testing the dome in fully assembled semiconductor fabrication equipment, and other post-process operations that will be apparent to those skilled in the art. After the post-process operations are completed, process 600 is completed with operation 616.

It will therefore be appreciated that a method for cleaning ceramic parts includes immersing a ceramic part into a first chemical bath to damage contaminant bonds, heating the ceramic part in a furnace after the contaminant bonds are damaged and immersing the ceramic part in a second chemical bath to remove contaminants. Also, the first chemical bath can be a dilute chemical bath including HF and HNO_3 which is heated to about 60-80°C.

Figure 7 is a flowchart showing a cleaning process 700, in accordance with one aspect of the present invention to remove particle from a textured high purity quartz surface. In an initial operation 701, pre-process operations are performed. Pre-process operations include determining the particular characteristics of the part to be processed and other pre-process operations that will be apparent to those skilled in the art.

In an operation 702, the high purity quartz part is DI water spray rinsed to remove loose polymers, particles and metallic impurities. Initially, the quartz part is unpacked, recorded, and photographed to record the initial condition of the dome. The quartz part is then placed in a chemical bath 703 and ultrasonicated for 15 min. The chemical bath is preferably a concentrated HF/HNO₃ chemical bath. The concentration of HF is about 25 %wt and HNO₃ about 35 %wt. The concentrated acid in the presence of ultrasonication energy dissolves a layer of damaged quartz to lower the particle counts on the quartz part surface. Thereafter it is removed from the chemical bath and DI spray rinsed in an operation 704.

Next, in a DI ultrasonication operation 706, the quartz is ultrasonicated in deionized water to further remove particles. Once a visual inspection 707 has been made of the quartz part, it is ultrasonicated in a fresh deionized water bath 707A for 15 min. If the part does not pass the visual inspection test, the part goes back to operation step 703 for additional cleaning. In the operation 708, the quartz is tested by LPC technique. As stated previously, this impurity testing operation helps in determining whether the part has been cleaned to have characteristics in accordance with the predetermined clean specification. If the particle level as measured by LPC technique is less than 200,000 particle per cm², the quartz part is then rinsed in deionized water approximately 10 times, and thereafter purged dry with filtered N₂ and further under a heat lamp for at least 1 hour in an operation 710. The process 706 can be repeated if the dome has not attained the specified levels of impurity

The part is then further tested for impurities, in a testing operation 712. Preferably, a surface particle test is performed on the dome using a Dryden QIII particle counter. After testing adequately to the predetermined specification, the part is packaged with cleanroom double bags in the cleanroom.

Finally, in operation 714, various post-process operations are performed. Post-process operations include testing the dome in fully assembled semiconductor fabrication equipment, and other post-process operations that will be apparent to those skilled in the art. After the post-process operations are completed, process 700 is completed with operation 716.

Figure 8 is a flowchart showing a cleaning process 800, in accordance with one aspect of the present invention to remove particle and metallic impurities from a textured high purity ceramic (>99% Al_2O_3) surface. In an initial operation 801, pre-process operations are performed. Pre-process operations include determining the particular characteristics of the part to be processed and other pre-process operations that will be apparent to those skilled in the art.

In an operation 802, the ceramic dome is DI water sprayed rinse to remove loose polymers, particles and metallic impurities. Initially, the ceramic dome is unpacked, recorded, and photographed to record the initial condition of the dome. The ceramic dome is then placed in a chemical bath 803 for about 2 hours. The chemical bath is preferably a concentrated $\text{H}_2\text{SO}_4/\text{H}_2\text{O}_2$ or $\text{H}_2\text{SO}_4/\text{H}_3\text{PO}_4$ chemical bath, which is heated to about 140-180°C. The concentration of H_2SO_4 is about 50 %wt, H_2O_2 is about 15 % wt and H_3PO_4 about 40 %wt. The hot concentrated acid dissolves a layer of damaged alumina to lower the particle counts on the dome surface. Thereafter it is removed from the chemical bath and DI spray rinsed in an operation 804.

Next, in a bath operation 806, the dome is placed in another chemical bath. The chemical bath is a dilute HF/HNO_3 chemical bath. The concentration of HF and HNO_3 is less than 5 %wt and 10 %wt respectively to remove metallic impurities. After this step, it is placed in an acid waste tank and rinsed with deionized water to remove any residual acids. Thereafter, the dome is preferably visually inspected to determine the cleanliness of the part. If the part still needs more cleaning, operation 806 is repeated.

In an ultrasonication operation 808, the dome is ultrasonicated in deionized water. Once a visual inspection has been made of the dome, it is ultrasonicated in a fresh overflowing deionized water bath for about two hours. In the operation 810, the dome is tested by LPC technique. As stated previously, this impurity testing operation helps in determining whether the part has been cleaned to have characteristics in accordance with the predetermined clean specification. If the particle level as measured by LPC technique is less than 500,000 particle per cm^2 , the dome is then rinsed in deionized water approximately 10 times, and thereafter purged dry with filtered N_2 and further under a heat lamp for at least 1 hour in an operation 812. The

process 808 can be repeated if the dome has not attained the specified levels of impurity.

The part is then further tested for impurities, in a testing operation 814. Preferably, a surface particle test is performed on the dome using a Dryden QIII
5 particle counter. After testing adequately to the predetermined specification, the part is packaged with cleanroom double bags in the cleanroom.

Finally, in operation 816, various post-process operations are performed. Post-process operations include testing the dome in fully assembled semiconductor fabrication equipment, and other post-process operations that will be apparent to those
10 skilled in the art.

In view of the foregoing it will be appreciated that a method for cleaning textured quartz parts includes immersing a textured quartz part into an ultrasonic chemical bath, immersing the textured quartz part into an ultrasonication water bath and immersing said textured quartz part into a deionized water bath. The method can
15 also include immersing the part in an ultrasonification overflowing bath.

It will further be appreciated that a method for determining the cleanliness of semiconductor fabrication equipment parts includes testing the parts before a cleaning process for at least one of particles, metallic impurities and organics. The parts are tested after certain steps in the cleaning process for at least one of particles, metallic
20 impurities and organics. The parts are tested a final time after a final cleaning step for at least one of particles, metallic impurities and organics.

Also, a method for removing particles on a textured surface of a semiconductor fabrication equipment part includes determining a chemical bonding characteristic of the particles, identifying a type of particles embedded in the textured
25 surface, measuring a depth of any subsurface damage and performing a combination of ultrasonication and chemical etching to the textured surface.

While the present invention has been described in terms of several preferred embodiments, there are many alterations, permutations, and equivalents which may fall within the scope of this invention. It should also be noted that there are many
30 alternative ways of implementing the methods and apparatuses of the present

invention. It is therefore intended that the following appended claims be interpreted as including all such alterations, permutations, and equivalents as fall within the true spirit and scope of the present invention.

CMTRP005A/PLH/JPK